

HDI-4124

The HDI-4124 Amplifier Splitter allows two HDMI devices to be switched easily into up to HDTV HDMI compatible monitors or projectors. Simply connect your HDTV to one of the HDI-4124 display outputs.

The HDMI Splitter can also be placed at the end of a long HDMI cable run to regenerate the HDMI signal.

The HDMI Amplifier Splitter offers solutions for HDTV retail and show site, HDTV, STB, DVD and Commercial Projector, noise space and security concerns, data center control, information distribution, conference room presentation, school and corporate training environments.

Features

The HDI-4124 Amplifier Splitter has many features that provides superior performance.

Easy to Use: Installs in seconds, no need user settings required.

Switching: Input can be switched between two HD sources..

Supports the Video Amplifier Bandwidth up to 2.25Gpbs/225MHz

HDCP support

FCC CE Certified

SPECIFICATIONS

Signal Inputs/Output	
Input Video Signal	0.5-1.0 volts p-p
Input DDC Signal	5 volts p-p (TTL)
Video Amplifier Bandwidth	2.25Gpbs/225MHz
Vertical Frequency Range	60Hz
HDMI Compliance	HDMI 1.3b
Resolutions(HDTV)	
Interlaced(50&60Hz)	480i,576i,1080i
Progressive(50&60Hz)	480p,576p,720p,1080p
Limited Warranty	1 Year Parts and Labor
Operating Temperature	0°C to +70°C
Operating Humidity	10% to 80 % RH (no condensation)
Storage Temperature	-10°C to +80°C
Storage Humidity	5% to 90 % RH (no condensation)
External Power Supply	5V DC@2*2(2A),2*4(2.5A);2*8(3A)
Power Consumption	15 Watts (max.)
Converter Unit	FCC,CE,UL
Power Supply	UL,CE,FCC