

J-Line™ Interconnection Systems

Cable Bushings for J-Line™ Plugs and Connectors

Boxed catalog numbers are standard bushing sizes. To order non-standard bushing, specify as follows: example JPS634H/JG65.



Standard Cable Bushings —
Size No. 3, 6, 10 and 20



Oversize Cable Bushings —
Size No. 3, 6, 10 and 20

HOLE DIAMETER FOR CABLE	SIZE 3 30 AMP	SIZE 6 60 AMP	SIZE 10 100/150 AMP	SIZE 20 200/270 AMP
.375"	JG31			
.500"	JG32			
.563"	JG325			
.594"	JG32B			
.625"	JG33	JG63		
.750"	JG34	JG64	JG104	
.781"	JG341			
.875"	JG35	JG65	JG105	
.938"	JG355			
1.000"	JG36*	JG66	JG106	JG206
1.125"	JG361*			
1.188"		JG67	JG107	JG207
1.313"			JG108	JG208
1.375"		JG69*		
1.500"		JG610*	JG1010	JG2010
1.688"			JG1011	JG2011
1.813"				JG2012
1.875"			JG1013*	
2.000"				JG2014
2.125"				JG2015
2.500"				JG2016*

Notes:

Boxed numbers denote standard bushing size supplied.

When ordering, select bushing size slightly larger than your cable O.D. for best fit.

Material — Neoprene.

Identification letter inside hole.